## **DIMMING WITH 1-CHANNEL OCCUPANCY DETECTOR AS MASTER**

(MOTION DETECTOR FOR INSIDE USE)

# **LUXOMAT® PD4-M-DIM-SM/-FC/-FM**



























#### **■ TECHNICAL DATA**

230 V~ ±10 %

O 360°

seated across

Ø 6.40 m Ø 24.00 m Ø 8.00 m

towards SM = IP54: FC/FM = IP20 /Class II / C€

**SM** Ø 101 x H 76 mm FC Ø 97 x H 103 mm FM Ø 97 x H 84 mm

IP 🗆

-25°C to +50°C

Housing UV- and shockresistant Polycarbonate

IR-PDim, IR-PD-DIM-Mini

#### Channel 1 (Control the lighting) 2300 W, $\cos \varphi = 1$ ;

1150 VA,  $\cos \varphi = 0.5$ 

1 min. - 30 min. or impulse




10 - 2000 Lux



1-10 VDC, max. 50 EB's

### (i) PRODUCT INFORMATION

- Remote controllable occupancy detector for inside use LUXOMAT® PD4-M-DIM as dim version for surface, false ceiling and flush mounting with circular detection area and range of 24 m
- An easy and cost effective way to realize a constant light control
- One channel to switch the lighting
- 1 dim output with 1-10 VDC interface to control electronic ballasts
- The connection of a unlimited number of slaves for reasonable extension is possible!
- Function full automatic or semi automatic mode, dimming and switching with the optional infrared remote control **LUXOMAT® IR-PDim**
- Typical applications: monitoring of large areas like underground garages, gyms, warehouses, loading ramps, halls



92098

92199

92206

- 1 Walking towards
- 2 Walking across
- 3 Seated activity

#### ACCESSORY (OPTIONAL)

LUXOMAT® IR-PD-DIM-Mini

Wire basket BSK

Covering IP23



grey

white

transparent

